



Electromagnetic Braking System

Dhammadip Kamble^{#1}, Suraj Taware^{#2}, Suraj Wabale^{#3}, Mayur Pawar^{#4}, Rushikesh Korake^{#5}

(Department of Mechanical Engineering, Smt. Kashibai Navale Clg Of Engineering, Savitribai Phule Pune University, India)

¹Dhammadip.kamble_skncoe@sinhgad.edu

²surajtaware2000@gmail.com

³surajwabale74@gmail.com

⁴mayurkpwr2000@gmail.com

⁵rushikorake123@gmail.com

Abstract

In this paper we had develop the electromagnetic braking system. Braking System should ensure the safety and comfort of the passenger, driver and other road user. The brake must be strong enough to stop the vehicle during emergency within shortest distance. The conventional braking system are bulky and power to weight ratio is low. Electromagnetic braking system is high-tech braking system find its use in small & heavy vehicle like car, jeep, truck, busses etc. This paper represent about minimizing the brake failure in order to avoid the accident. It also reduces the maintenance of braking system. The effectiveness of brake should remain constant. The proper cooling of brake gives anti fade character and efficient operation of brake. Proper lubrication and maintenance must be done to operate brake safe, effective and progressive with minimum fatigue to driver. This system provides better response time for emergency situations and in general keeps the friction brake working longer and safer.

Keyword- Brake, Electromagnetism, Brake power, Torque

Introduction

Electromagnetic brakes have been used as supplementary retardation equipment in addition to the regular friction brakes on heavy vehicles. We outline the general principles of regular brakes and several alternative retardation techniques in this section. The working principle and characteristics of electromagnetic brakes are then highlighted. The principle of braking in road vehicles involves the conversion of kinetic energy into thermal energy (heat). When stepping on the brakes, the driver commands a stopping force several times as powerful as the force that puts the car in motion and dissipates the associated kinetic energy as heat. Brakes must be able to arrest the speed of a vehicle in a short periods of time regardless how fast the speed is. As a result, the brakes are required to have the ability to generating high torque and absorbing energy at extremely high rates for short periods of time. Brakes may be applied for a prolonged periods of time in some applications such as a heavy vehicle descending a long gradient at high speed. Brakes have to have the mechanism to keep the heat absorption capability for prolonged periods of time. In the electromagnetic brake, the coil or solenoid attracts a steel disc. The steel disc presses a brake disc made of sintered or asbestos material between itself and a stationary steel disc. The torque is thus 'grounded' and braking action takes place. This type of brake is used in machines like lathes, presses etc. In electro-magnetic braking system electro-magnetic property is used due to this action of braking will be done. In this system, electro magnet iron plate, liners, tension spring, stud, disc brake plate are used. The brake liners are attached with electro- magnet and iron plate individually and both plate insert the disc plate and this plate rigidly attached with wheels. The battery of minimum 12 volt is used for external power supply. Electromagnet consists of wire wound over a soft iron core. When current is passed through the coil, it produces a magnetic field which magnetizes the core into the bar magnet with the polarities. Strong magnetic field is obtained by high currents of large self-induction. High currents are not always feasible, which is why a high self-induction is obtained by making a loop of wire in the shape of a coil, a so-called solenoid. More current and more turns produce a stronger magnetic field which results in stronger electromagnet. When current is switched OFF field disappears and the iron core no longer a magnet. This ability of an

electromagnet provides a strong magnetic force of attraction. Shape geometry and material used in construction of electromagnet decide the shape and strength of magnetic field produced by it.

Construction and working:-




Fig. 1 Electromagnetic Braking System

Nomenclature V=Initial

velocity U=Final velocity

A=Deceleration of rotating mass

F=Braking force

T=Braking torque H=magnetic
field length

N= No. of turns/ length of solenoid

C=clamping force

P=average power K.E=kinetic
energy

Assume data

Sr. No.	Notations	Value	Meaning
1	M	12kg	Rotating mass
2	t	2.5 sec	Braking time
3	d	0.276m	Wheel dia.
4	N	150rpm	Wheel rotational speed
5	R	1.725	Ratio of wheel diameter& disc diameter
6	R _d	0.08m	Disc radius
7	μ	0.25	Coefficient of friction
8	R _e	0.06m	Effective disc radius
9	E	29.0 joules	Total energy of rotating mass
10	I	8 Amp-hr	Current through coil
11	L	0.048m	Length of solenoid
12	□	59.6 x 10 ⁶ S/m	Electrical conductivity of disc
13	R	0.015m	Radius of electromagnet
14	V	12	Battery Voltage
15	I	8Amp-Hr	Battery Current
16	C	465 J/Kg ⁰ C	Sp. Heat capacity of disc
17	K	54 watt/m ⁰ C	Thermal conductivity of disc
18	Volume	0.00003601m ³	Disc volume
19	P	7850 kg/ m ³	Density of disc
20	μ _o	4π x 10 ⁻⁷	Permeability of air
21	μ _s	2000	Permeability of steel

Braking force

The total braking force required can simply be calculated using Newton's Second Law. $V = \Pi$

$$*d*N/60 = (\Pi \times 0.276 \times 150)/60 = 2.1666 \text{ m/sec}$$

$$A = (v-u)/t = (2.1666-0)/2.5 = 0.86664 \text{ m/sec}^2 \text{ F=}$$

$$m*A = 12 \times 0.867 = 10.40\text{N}$$

Braking force

$$T = (F \times 0.5d)/R$$

$$= (10.40 \times 0.5 \times 0.276)/1.725 = 0.832 \text{ Nm}$$

Clamp force

$$C = T / (\mu \times R_e)$$

$$= 0.832 / (0.25 \times 0.06) = 55.46 \text{ N}$$

Brake power

Assuming the stop is from the test speed down to zero then the kinetic energy is given by: - $KE = 0.5$

$$m \times v^2$$

$$= 0.5 \times 12 \times 2.1666^2 = 28.149336 \text{ Joules}$$

Rotational Energy:

The rotational energy is the energy needed to slow rotating parts. It varies for different vehicles and which gear is selected however taking 3% of the kinetic energy is a reasonable assumption. The power is then given by:

$$P = E/t = 29.0/2.5 = 11.61 \text{ watt}$$

This is the average power. The peak power at the time of braking is double of this.

Brake heating**Fade Stop Temperature Rise**

$$\Delta t = (P \times t) / (\rho \times c \times \text{Volume})$$

$$= (11.61 \times 2.5) / (7850 \times 465 \times 3.601 \times 10^{-5}) = 1.0190^\circ \text{C}$$

Magnetic flux density (B):

$$T = \frac{1}{2} \times \Sigma \delta \quad \pi \times R^2 \times m^2 \times B^2 \times z^2 [1 - \dots]$$

$$= (0.5 \times 59.6 \times 10^6 \times 0.003 \times 5\pi^2 \times 0.015^2 \times 0.007^2 \times B^2) \times (1 - (0.035/0.996)) = 18.01 \text{ Wb/m}^2.$$

$$B = (\mu_s \times \mu_o \times n \times I) / L$$

$$18.01 = (2000 \times 4\pi \times 10^{-7} \times n \times 8) / 0.048$$

$$N = 43 \text{ turns/m}$$

Magnetic field strength (H):

$$H = N \times I / L$$

$$= (43 \times 8) / 0.048 = 7166.66 \text{ A/m}$$

Result

By using the electromagnetic brake as supplementary retardation equipment, the friction brakes can be used less frequently, and therefore practically never reach high temperatures. The brake linings would last considerably longer before requiring maintenance, and the potentially “brake fade” problem could be avoided. In research conducted by a truck manufacturer, it was proved that the electromagnetic brake assumed 80 percent of the duty which would otherwise have been demanded of the regular service brake (Reverdin 1974). Furthermore, the electromagnetic brake prevents the dangers that can arise from the prolonged use of brakes beyond their capability to dissipate heat. This is most likely to occur while a vehicle descending a long gradient at high speed. The installation of an electromagnetic brake is not very difficult. It does not need a subsidiary cooling system. It does not effect on the efficiency of engine. electromagnetic brake also has better controllability. Thermal stability of the electromagnetic brakes is achieved by means of the convection and radiation of the heat energy at high temperature. The electromagnetic brakes has excellent heat dissipation efficiency. Electromagnetic brakes have better thermal dynamic performance than regular friction brakes.

Conclusion

As we discussed about the limitations of drum brakes, hydraulic brakes and pneumatic brakes electromagnetic brake is a better and reliable solution. Electromagnetic brake control system is an electric switching system which gives it superior controllability. The installation of an electromagnetic brake is not very difficult. From the foregoing, it is apparent that the electromagnetic brake is an attractive complement to the safe braking of heavy vehicles. Good results with current design, a larger budget would improve performance.

Reference

- 1) Dr Kirpal Singh. Automobile Engineering and Technology, Vol 1
- 2) R.A. Barapate "Electromagnetic Engineering" Technova Educational Publication
- 3) Khurmi & Gupta "Machine Design" S Chand Publication.
- 4) V.B. Bhandari "Design of Machine Elements" Tata McGraw Hill.
- 5) K. Balaveera Reddy. "Design data hand-book for mechanical engineering.
- 6) Flemming, Frank; Shapiro, Jessica (July 7, 2009). "Basics of Electromagnetic Brakes" .machine design : pp. 57–58
- 7) Kren, Lawrence; Flemming, Frank (August 5, 1999). "Getting a Handle on Inertia" .machine design: pp. 92–93.
- 8) Auguston, Karen; Flemming, Frank (September 1999). "Floating Armature Speeds Response" .Global Design News: pp. 46–47.
- 9) Zalud, Todd; Flemming, Frank (September 9, 1999). "Getting a Grip on Brake Selection" .machine design: pp. 83–86.
- 10) Electromagnetic Compatibility, design handbook series 1.0. John Wiley & Sons.