



Quantum-Scale Charge Transport in Nanostructured Materials for Advanced Energy Storage Applications

Dr. Deepa Khatik

¹Asstt. Prof., Dept. of Physics, Govt. Auto. Girls P. G. College, Sagar M. P.,
bhojakdeepa3@gmail.com, India;

Abstract

Charge transport at the nanoscale limits the power density, rate capability and cycle life of electrochemical energy storage devices. This paper proposes the Series-Bottleneck Quantum Transport (SBQT) model, which joins confinement-shifted conduction, WKB tunnelling across conductor junctions, percolation, ion diffusion and interfacial charge transfer into one set of seven equations and a short algorithm. The model returns a time constant for each transport step and the net capacity delivered at any C-rate. Applied to a representative low-conductivity oxide cathode, it shows that the limiting step switches from the electron network to ion diffusion at a particle size of about 50 nm; that each 0.1 nm of junction gap raises junction resistance by a factor of 2.8; and that the optimum particle size falls from about 27 nm at 1C to 13 nm at 10C when the network is good, but stays near 22 nm when the network is poor. Sensitivity analysis ranks conductor loading, ion diffusivity and junction barrier as the levers with the largest effect. The paper gives a validation route based on standard measurements, and the 128-line Python code is provided for reproduction.

Keywords: quantum transport; nanostructured electrodes; Landauer formalism; density functional theory; MXenes; graphene; supercapacitors; lithium-ion batteries; energy storage

1. Introduction

Energy storage performance is limited by how fast charge can move, not only by how much can be stored. In a battery or supercapacitor electrode, an electron must travel through the active material and conductive network, while a compensating ion must diffuse through the electrolyte, cross the interface and enter the host lattice. The slower of these processes governs the rate capability.

Nanostructuring shortens diffusion lengths and raises surface area, which is why it has been central to electrode design for two decades (Ari  et al., 2005). Below roughly 10 to 20 nm, however, classical drift-diffusion descriptions begin to fail. Quantum confinement reshapes the density of states, tunnelling opens conduction across thin barriers, and surface and defect states dominate carrier behaviour. These effects can raise or lower conductivity by orders of magnitude, depending on how the structure is built.

1.1 Research gap

Most electrochemical studies report capacity and cycling data and infer transport indirectly. Most theoretical studies compute band structures or single-particle barriers but do not link them to device-level rate performance. A unified treatment that connects quantum-scale transport to electrode architecture and to measurable device metrics is still lacking.

1.2 Objectives

1. Review the physical models that describe electron and ion transport at the nanoscale.
2. Compare how the main nanostructured material families exhibit these regimes.
3. Develop the SBQT model, a compact structure-transport-performance model with an algorithm and flow chart.
4. Use the model to identify the limiting transport step, the optimum particle size and the most sensitive design levers, and to propose a validation route.

2. Theoretical Background

The appropriate transport model depends on how the electron's phase-coherence length compares with the size of the nanostructure. Three regimes cover most electrode materials.

2.1 Coherent (ballistic) transport

When the conductor is shorter than the mean free path and phase-coherence length, conductance follows the Landauer formula (Landauer, 1957; Büttiker, 1986):

$$G = \frac{2e^2}{h} \sum_n T_n(E_F)$$

Here G is the conductance, e the electron charge, h Planck's constant, and T_n the transmission probability of channel n at the Fermi energy. Each fully open channel contributes one conductance quantum, $2e^2/h$ (about $77.5 \mu\text{S}$). Nanotubes, nanoribbons and atomically thin sheets can approach this limit over short lengths.

2.2 Quantum confinement and density of states

Confinement in one, two or three dimensions discretises the energy spectrum. For a particle in a box of width L , energy levels scale as $1/L^2$, so a decrease in size widens band gaps and shifts band edges. This changes carrier density, thermodynamic potential and reaction voltage. It also produces sharp features in the density of states, which can enhance quantum capacitance in low-dimensional carbon electrodes.

2.3 Incoherent transport: hopping and polaron conduction

In disordered oxides, amorphous films and particle networks, carriers move by thermally activated hopping. Two models are used:

- **Small-polaron (Marcus-type) hopping**, where the rate depends on the reorganisation energy λ and the site-to-site coupling. Conductivity is thermally activated, as in LiFePO_4 and many transition-metal oxides.
- **Variable-range hopping (Mott, 1968; Efros and Shklovskii, 1975)**, where conductivity follows a stretched-exponential temperature dependence in strongly localised systems:

$$\sigma(T) = \sigma_0 \exp \left[- \left(\frac{T_0}{T} \right)^{1/(d+1)} \right]$$

where d is the dimensionality. The exponent $1/(d+1)$ applies to Mott hopping ($1/4$ in three dimensions); Efros-Shklovskii hopping, which includes Coulomb interactions, gives an exponent of $1/2$.

2.4 Ionic transport and mixed conduction

Ion motion is thermally activated across migration barriers, and diffusivity follows an Arrhenius relation, $D = D_0 \exp(-E_a / k_B T)$. In nanoscale ionics, space-charge layers at interfaces can change carrier concentration by orders of magnitude, a size effect described as nanoionics (Maier, 2005). Electrode performance depends on ambipolar (coupled electron and ion) transport, so the slower carrier controls the effective rate.

2.5 Computational description

Density functional theory (Hohenberg and Kohn, 1964; Kohn and Sham, 1965) provides electronic structure and migration barriers, for example through nudged-elastic-band calculations. Coupling DFT with non-equilibrium Green's functions gives the transmission function $T(E)$ for a junction or interface under bias, from which current follows by integrating over the Fermi window.

3. Nanostructured Materials

Four material families dominate nanostructured storage electrodes. They differ mainly in which transport regime limits performance.

Family	Examples	Dominant electronic transport	Main limitation	Typical role
Carbon nanostructures	Graphene, carbon nanotubes, porous carbon	Near-ballistic along tubes and sheets; junction-limited across networks	Inter-particle contact resistance; low volumetric capacity	Conductive scaffold, double-layer electrode
2D layered materials and MXenes	MoS ₂ , Ti ₃ C ₂ T _x (Naguib et al., 2011)	Metallic or semimetallic in-plane; hopping between flakes	Restacking; terminal-group effects on conductivity	Intercalation and pseudocapacitive electrode
Transition-metal oxides and phosphates	LiFePO ₄ , TiO ₂ , MnO ₂ , V ₂ O ₅	Small-polaron hopping; wide-gap semiconducting	Low intrinsic electronic conductivity, roughly 10^{-9} to 10^{-5} S/cm (approximate literature range)	High-capacity active material
Hybrid nanocomposites	Oxide on graphene, MXene-polymer, core-shell particles	Percolative network with tunnelling at interfaces	Interface control and reproducibility	Combines capacity with conductivity

3.1 Carbon nanostructures

Graphene and carbon nanotubes show high carrier mobility and long mean free paths (Novoselov et al., 2004). The intrinsic channel is rarely the bottleneck. Transport across tube-tube or sheet-sheet junctions, where carriers tunnel through a thin gap, sets the network resistance. In graphene the density of states is low near the Dirac point, so quantum capacitance can limit total capacitance in thin electrodes.

3.2 Two-dimensional materials and MXenes

MXenes such as Ti₃C₂T_x combine metallic-like in-plane conduction with a hydrophilic, ion-accessible surface. Their conductivity depends strongly on the surface terminations (–O, –OH, –F) and on flake size, because flake-to-flake hopping dominates films. Ions intercalate between layers, so interlayer spacing controls ion diffusion.

3.3 Oxides and phosphates

These materials store the most charge per unit volume but conduct poorly. Nanosizing shortens the ion path, and carbon coating or doping raises electronic conductivity. In LiFePO₄, nanoscale particles and a thin carbon shell moved the material from a laboratory curiosity to a commercial cathode (Goodenough and Park, 2013).

3.4 Hybrid nanocomposites

Hybrids place a high-capacity phase in contact with a conductive one. The interface then decides the outcome: band alignment sets the barrier, and interfacial dipoles or charge transfer can either assist or block carrier injection. Because the conducting phase must form a continuous network, percolation theory sets the minimum loading needed for a connected electronic path.

4. Methodology: the SBQT Model

This work introduces a compact design model, called the Series-Bottleneck Quantum Transport (SBQT) model. It joins three layers that are usually treated separately: a quantum layer (confinement and tunnelling), a network layer (percolation), and a kinetic layer (diffusion and interfacial charge transfer). Each layer gives a time constant, the time constants add in series, and the sum predicts delivered capacity at any C-rate. The whole model runs in under a second on a laptop, so design maps can be swept and checked against experiments.

4.1 System and assumptions

The electrode is a composite of spherical active nanoparticles of diameter L , a conductive nanoparticle network of volume fraction ϕ and particle size d_c , and an electrode thickness ℓ . Adjacent conductor particles are separated by an average junction gap g . Assumptions: (i) single-particle, first-order charging kinetics; (ii) an interfacial barrier E_b that controls the exchange current; (iii) uniform particle size; (iv) isothermal operation at 298 K.

4.2 Governing equations

Quantum layer. Confinement raises the activation energy of hopping conduction in the active phase, and a WKB tunnelling barrier sets the resistance of each conductor junction:

$$\Delta E(L) = \frac{3\hbar^2\pi^2}{2m^*L^2}, \quad \sigma_a(L) = \sigma_0 \exp\left[-\frac{E_{a0} + \Delta E(L)}{k_B T}\right]$$

$$\kappa = \frac{\sqrt{2m_e\phi_b}}{\hbar}, \quad R_j(g) = \frac{h}{2e^2} e^{2\kappa g}$$

Network layer. Junction conductivity feeds a percolating network, and the electrode conducts through the network and the active phase in parallel:

$$\sigma_{net} = \frac{1}{R_j d_c} \left[\frac{\phi - \phi_c}{1 - \phi_c} \right]^t, \quad \sigma_{eff} = \sigma_{net} + (1 - \phi) \sigma_a$$

Kinetic layer. Three time constants describe ion diffusion, electron supply and interfacial charge transfer, with $C_v = Q_v / \Delta V_w$ the volumetric differential capacitance:

$$\tau_D = \frac{L^2}{\pi^2 D}, \quad \tau_E = \frac{\ell^2 C_v}{\sigma_{eff}}, \quad \tau_{ct} = \frac{C_v (k_B T / q) L}{6 i_0}, \quad i_0 = i_{00} e^{-E_b / k_B T}$$

Performance layer. The steps act in series, so their time constants add. For a discharge of duration $T_d = 3600 / C$ seconds, first-order kinetics give the fraction of capacity that is reached, and small particles pay a penalty for irreversible surface loss:

$$\tau = \tau_D + \tau_E + \tau_{ct}$$

$$R(C) = 1 - \frac{\tau}{T_d} \left[1 - e^{-T_d/\tau} \right]$$

$$Q_{net}(C, L, g) = R(C) \left(1 - \frac{6\delta}{L} \right), \quad L^*(C, g) = \arg \max_L Q_{net}$$

Symbols: m^* effective carrier mass, m_e electron mass, ϕ_b junction barrier height, ϕ_c percolation threshold, t percolation exponent, D lithium diffusivity, δ equivalent thickness of the layer consumed by irreversible surface reactions.

4.3 Algorithm

Algorithm SBQT-Optimise

Input : material set $P = \{D, \sigma_0, E_a, m^*, \phi_b, d_c, \phi, \phi_c, t, l, Q_v, dV_w, i_0, E_b, \delta\}$


grids for particle size L , junction gap g , C-rate list

Output: $R(C)$, Q_{net} , dominant bottleneck, optimum size $L^*(C, g)$

```

1 for each gap g in G:
2   R_j <- (h / 2e^2) * exp(2 * kappa * g)      # Eq. 2
3   sig_net <- (1 / (R_j * d_c)) * ((phi - phi_c)/(1 - phi_c))^t # Eq. 3
4   for each size L in Lgrid:
5     dE <- 3 hbar^2 pi^2 / (2 m* L^2)          # Eq. 1
6     sig_a <- sigma0 * exp(-(Ea0 + dE) / kT)
7     sig_eff <- sig_net + (1 - phi) * sig_a
8     tau_D, tau_E, tau_ct <- Eq. 4
9     tau <- tau_D + tau_E + tau_ct              # Eq. 5
10    for each C in C-rates:
11      T_d <- 3600 / C
12      R <- 1 - (tau / T_d) * (1 - exp(-T_d / tau)) # Eq. 6
13      Q <- R * (1 - 6 * delta / L)                # Eq. 7
14      record bottleneck = argmax(tau_D, tau_E, tau_ct)
15 for each (C, g): L* <- argmax_L Q
16 return tables, maps, L*
```

4.4 Flow chart



The loop returns to the design vector, so the same chart serves for a single evaluation, a grid sweep or an optimiser such as differential evolution.

4.5 Baseline parameters

The baseline represents a phosphate or oxide cathode with poor intrinsic conductivity. Values are representative assumptions within the range reported for such materials, and each maps to a measurement that can replace it.

Parameter	Symbol	Baseline	Replace with measured value from
Li ⁺ diffusivity	D	$1 \times 10^{-14} \text{ cm}^2/\text{s}$	GITT, EIS
Conductivity prefactor, activation energy	σ_0, E_{a0}	10^3 S/cm , 0.45 eV	Temperature-dependent four-probe
Carrier effective mass	m^*	$3 m_e$	DFT band structure, polaron fits
Junction barrier	ϕ_b	1.0 eV	UPS or STS at the interface
Conductor size, fraction, threshold	d_c, ϕ, ϕ_c	30 nm, 0.06, 0.02	TEM, weighing, percolation curve

Parameter	Symbol	Baseline	Replace with measured value from
Percolation exponent	t	2.0	Conductivity vs. loading fit
Electrode thickness	ℓ	50 μm	Cross-section SEM
Volumetric capacity, voltage window	$Q_v, \Delta V_w$	1440 C/cm ³ (400 mAh/cm ³), 0.5 V	Cycling data
Exchange-current prefactor, barrier	i_{00}, E_b	10^{-4} A/cm ² , 0.10 eV	Temperature-dependent EIS
Irreversible-loss layer	δ	0.2 nm	First-cycle coulombic efficiency

4.6 Feasibility and validation

The model needs no supercomputer: the full study in Section 5 was computed by a script of about 130 lines of Python (numpy only), which is attached with the paper for reproducibility. Validation follows a three-step path: (1) measure the parameters in the last column above on one reference electrode; (2) predict its rate curve with Eqs. 1 to 7 without fitting; (3) compare with measured discharge capacity at 0.5C to 20C and refine the parameters with the largest sensitivity (Section 5.5). Agreement within about 10% capacity would support the model; larger deviations point to the missing physics, for example particle-size distribution or electrolyte limitations.

5. Results and Discussion

All results below are outputs of the SBQT model (Eqs. 1 to 7) with the baseline parameters of Section 4.5. They are model predictions, not measurements, and they show how transport physics shapes electrode design. Three findings stand out: the limiting step switches from electrons to ions at a particle size of about 50 nm; each 0.1 nm of junction gap costs a factor of 2.8 in junction resistance; and the best particle size falls from about 27 nm at 1C to about 13 nm at 10C only when the conductive network is good.

5.1 Junction tunnelling controls the electron supply

Because the tunnelling resistance depends exponentially on gap, the network is the most sensitive part of the electrode. With $\phi_b = 1.0$ eV, $\kappa = 5.12$ nm⁻¹, so every 0.1 nm of extra gap multiplies R_j by $e^{(2\kappa \cdot 0.1 \text{ nm})} = 2.8$.

Table 1. Junction resistance and network conductivity versus gap ($\phi = 0.06$)

Gap g (nm)	R_j (M Ω)	σ_{net} (S/cm)
0.3	0.28	2.0×10^{-3}
0.4	0.78	7.1×10^{-4}
0.5	2.2	2.6×10^{-4}
0.6	6.0	9.2×10^{-5}
0.8	47	1.2×10^{-5}
1.0	364	1.5×10^{-6}


A gap of 1.0 nm makes the network about 1300 times less conductive than a gap of 0.3 nm. The intrinsic conductivity of the active phase (about 2×10^{-5} S/cm at $L \geq 50$ nm) is comparable to a poorly connected network, so the network is the main electronic pathway only for gaps below about 0.7 nm.

5.2 The limiting step switches with particle size

Table 2. Time constants at $g = 0.5 \text{ nm}$

L (nm)	$\tau_{\text{D ion}}$ (s)	$\tau_{\text{E electron}}$ (s)	$\tau_{\text{ct interface}}$ (s)	Total τ (s)	Dominant step
10	10	261	6	277	Electron network
20	41	258	12	311	Electron network
50	253	258	30	541	Ion and electron equal
100	1013	258	61	1332	Ion diffusion
200	4053	258	121	4432	Ion diffusion

Which step limits transport? ($g = 0.5 \text{ nm}$)




The electron time τ_{E} is nearly independent of L because it is set by the network, while τ_{D} grows as L^2 . The two cross where $L = \pi \sqrt{D \cdot \tau_{\text{E}}}$, which is 50 nm here. Below this size, shrinking particles further gives little benefit, and the network becomes the target. Confinement itself has a negligible effect in this range: ΔE is about 4 meV at 10 nm and rises to about 0.4 eV only near 1 nm, so quantum size effects on conductivity matter for sub-5 nm structures, whereas tunnelling at junctions matters at every size.

5.3 Rate capability

Table 3. Net delivered capacity (% of theoretical) at $g = 0.5 \text{ nm}$


L (nm)	0.5C	1C	2C	5C	10C	20C
10	84.6	81.2	74.5	56.7	38.8	23.3
20	89.9	85.9	77.8	57.4	38.3	22.6

L (nm)	0.5C	1C	2C	5C	10C	20C
50	90.3	82.9	69.3	43.6	26.3	14.6
100	80.6	64.7	44.6	22.5	12.2	6.4
200	50.3	31.3	17.7	7.7	3.9	2.0



At 0.5C a 50 nm particle delivers the most capacity (90.3%), but at 5C the 20 nm particle leads (57.4% against 43.6%). The 10 nm particle never leads, because irreversible surface loss (12% at 10 nm) offsets its faster ion transport, and its electrons are limited by the network anyway.


5.4 Design map and optimum particle size



The map shows a plateau at small L and small g , reaching about 83% at $g = 0.3$ nm and $L \approx 15$ nm. Moving up the map (larger gap) lowers capacity at every particle size, and above $g \approx 0.7$ nm no particle size gives more than about 20% at 5C. The optimum size L^* depends on network quality:

Table 4. Optimum particle size L^* (nm) and its net capacity (%)

C-rate	$g = 0.4$ nm	$g = 0.5$ nm	$g = 0.7$ nm
1C	26.8 (90.6%)	26.3 (86.3%)	27.1 (61.5%)
2C	20.8 (86.2%)	20.4 (77.8%)	24.3 (42.1%)
5C	14.8 (75.5%)	15.3 (58.0%)	22.8 (21.1%)
10C	11.8 (61.5%)	13.6 (39.3%)	22.3 (11.5%)
20C	10.1 (43.7%)	12.7 (23.5%)	22.3 (6.0%)



With a good network, L^* shrinks as the C-rate rises, since ion diffusion becomes the constraint. With a poor network ($g = 0.7$ nm), L^* stays near 22 nm because electrons, not ions, limit the device, and making particles smaller only adds surface loss. This is the main design message: reduce the gap before reducing the particle size.

5.5 Sensitivity

Table 5. Change in net capacity at 5C ($L = 50$ nm, $g = 0.5$ nm; baseline 43.6%)

Parameter varied	Low case	High case	Capacity range (%)	Swing (points)
Conductor fraction ϕ ($\pm 50\%$)	15.0	54.4	15.0 to 54.4	39.4
Li^+ diffusivity D ($\pm 50\%$)	33.4	48.5	33.4 to 48.5	15.1
Junction barrier ϕ_b ($\pm 20\%$)	49.6	37.3	37.3 to 49.6	12.3
Interfacial barrier E_b (± 0.05 eV)	45.0	35.8	35.8 to 45.0	9.2
Exchange prefactor i_{00} ($\pm 50\%$)	42.1	44.2	42.1 to 44.2	2.1
Conductivity prefactor σ_0 ($\pm 50\%$)	43.1	44.2	43.1 to 44.2	1.1

The loading of the conductive phase dominates because it sets both the percolation margin and the electron time. Diffusivity and junction barrier follow. The active-phase conductivity barely matters once a network exists, which supports the strategy of putting engineering effort into the network and its junctions.

5.6 Limits of the model

The model uses a single particle size, a first-order rate law and series time constants, so it will underestimate performance where electrolyte transport or particle-size distribution matters and overstate it where side reactions are severe. Its role is to rank design levers and locate optima; absolute capacities need calibration against measured data, as described in Section 4.6.

6. Energy Storage Applications

Device	Transport-limited step	Role of nanoscale transport engineering
Lithium-ion batteries	Electron transport in oxide cathodes; Li^+ diffusion in graphite and silicon	Carbon-coated nanoparticle cathodes; porous or nanostructured silicon that accommodates volume change
Sodium-ion and multivalent batteries	Slow diffusion of larger or more highly charged ions	Expanded interlayer spacing in layered hosts; shorter diffusion paths
Supercapacitors	Ion access to surface; quantum capacitance in low-density-of-states carbons	Hierarchical pores, MXene and graphene films with controlled spacing, pseudocapacitive oxides (Simon and Gogotsi, 2008)
Solid-state batteries	Ion conduction across solid-solid interfaces and grain boundaries	Interface coatings, nanoscale buffer layers, space-charge control
Hybrid capacitors	Mismatched kinetics between battery-type and capacitor-type electrodes	Balancing charge transport in both electrodes

Across these devices the same logic holds: identify the slowest carrier, then reshape the nanostructure to accelerate it without sacrificing volumetric energy density. In solid-state systems the interface replaces the electrolyte bulk as the main design target, which makes nanoscale interfacial control the most active current research area.

7. Challenges and Future Outlook

Four obstacles stand between current understanding and predictive electrode design.

- **Scale bridging.** DFT-NEGF handles hundreds of atoms, while electrodes span micrometres. Machine-learned interatomic potentials and multiscale models are the most promising route to close this gap.
- **Operando measurement.** Transport parameters change with state of charge, temperature and ageing, yet most are measured ex situ. Operando conductive-AFM, spectroscopy and neutron methods are needed.
- **Reproducibility.** Surface terminations, defects and stacking vary between synthesis batches and dominate transport in nanomaterials. Reporting standards for conductivity and diffusion measurements would make data comparable.
- **Manufacturability.** Laboratory nanostructures must survive slurry processing, calendaring and cost constraints without losing the transport advantage.

Future work should couple high-throughput screening with machine learning to search for materials with low migration barriers and favourable band alignment, and should study interfaces in solid-state and multivalent systems, where quantum-scale effects are least understood.

8. Conclusion

The SBQT model shows that quantum-scale transport, in the form of junction tunnelling, decides how much capacity a nanostructured electrode delivers at high rate. Ion diffusion controls the device above a particle size of about 50 nm, while the conductive network controls it below that size, so the design order should be to shorten and tighten the electronic junctions first and to reduce particle size second. The optimum particle size is not fixed: it falls with C-rate only when the network is good. These conclusions are model predictions; calibrating the model on a measured reference electrode, as outlined in Section 4.6, is the next step toward device design.

References

The references below are standard works cited in the text. Verify each against the original source and add the papers most relevant to your own results before submission.

1. Ariçò, A. S., Bruce, P., Scrosati, B., Tarascon, J.-M., van Schalkwijk, W. (2005). Nanostructured materials for advanced energy conversion and storage devices. *Nature Materials*, 4, 366–377.
2. Büttiker, M., Imry, Y., Landauer, R., Pinhas, S. (1985). Generalized many-channel conductance formula with application to small rings. *Physical Review B*, 31, 6207. See also Büttiker, M. (1986), *Physical Review Letters*, 57, 1761.
3. Efros, A. L., Shklovskii, B. I. (1975). Coulomb gap and low temperature conductivity of disordered systems. *Journal of Physics C*, 8, L49.
4. Goodenough, J. B., Park, K.-S. (2013). The Li-ion rechargeable battery: a perspective. *Journal of the American Chemical Society*, 135, 1167–1176.
5. Hohenberg, P., Kohn, W. (1964). Inhomogeneous electron gas. *Physical Review*, 136, B864.
6. Kohn, W., Sham, L. J. (1965). Self-consistent equations including exchange and correlation effects. *Physical Review*, 140, A1133.
7. Landauer, R. (1957). Spatial variation of currents and fields due to localized scatterers in metallic conduction. *IBM Journal of Research and Development*, 1, 223–231.
8. Maier, J. (2005). Nanoionics: ion transport and electrochemical storage in confined systems. *Nature Materials*, 4, 805–815.
9. Mott, N. F. (1968). Conduction in glasses containing transition metal ions. *Journal of Non-Crystalline Solids*, 1, 1–17.
10. Naguib, M., Kurtoglu, M., Presser, V., et al. (2011). Two-dimensional nanocrystals produced by exfoliation of Ti_3AlC_2 . *Advanced Materials*, 23, 4248–4253.
11. Novoselov, K. S., Geim, A. K., Morozov, S. V., et al. (2004). Electric field effect in atomically thin carbon films. *Science*, 306, 666–669.
12. Simon, P., Gogotsi, Y. (2008). Materials for electrochemical capacitors. *Nature Materials*, 7, 845–854.